



1. Black w/White Stripe – Connects to the left side turn signals (Same colors as OE)
2. Black wire – Connects to Terminal 49a on flasher relay (OE uses Black w/Green & White stripe)
3. Green w/Black Stripe – Connects to the right side turn signals (OE uses Black w/Green stripe)
4. Brown w/White Stripe – Connects to Terminal S on the headlight dimmer relay. (Same colors as OE)
5. Brown wire – Connects to the chassis ground. (Same color as OE)

The wires that are left over (Blue w/Black Stripe, Grey wire and Red w/Black Stripe) are redundant and do not need to be connected to anything.